

Display type: Fujitsu PPF21C8060UA-92
 Cable no.: Not available
 System: 686LCD
 Display driver: 640x480 TFT18
 Status: Verified

Display (68-pole conn.)		Cable	JPLCD connector		Remarks
Pin no.	Function	Wire no.	Pin	Function	
1	DATA-R7	1	49	P23	
2	S.GND	2	*	GND	
3	DATA-R6	3	48	P22	
4	S.GND	4	*	GND	
5	DATA-R5	5	47	P21	
6	S.GND	6	*	GND	
7	DATA-R4	7	46	P20	
8	S.GND	8	*	GND	
9	DATA-R3	9	44	P19	
10	S.GND	10	*	GND	
11	DATA-R2	11	43	P18	
12	S.GND	12	*	GND	
13	DATA-R1	13	42	P17	
14	S.GND	14	*	GND	
15	DATA-R0	15	41	P16	
16	S.GND	16	*	GND	
17	DATA-G7	17	37	P15	
18	S.GND	18	*	GND	
19	DATA-G6	19	36	P14	
20	S.GND	20	*	GND	
21	DATA-G5	21	34	P13	
22	S.GND	22	*	GND	
23	DATA-G4	23	33	P12	
24	S.GND	24	*	GND	
25	DATA-G3	25	31	P11	
26	S.GND	26	*	GND	
27	DATA-G2	27	30	P10	
28	S.GND	28	*	GND	
29	DATA-G1	29	28	P9	
30	S.GND	30	*	GND	
31	DATA-G0	31	27	P8	
32	S.GND	32	*	GND	
33	N.C.	33	-	-	
34	N.C.	34	-	-	
35	DATA-B7	35	25	P7	
36	S.GND	36	*	GND	
37	DATA-B6	37	24	P6	

38	S.GND	38	*	GND	
39	DATA-B5	39	22	P5	
40	S.GND	40	*	GND	
41	DATA-B4	41	21	P4	
42	S.GND	42	*	GND	
43	DATA-B3	43	19	P3	
44	S.GND	44	*	GND	
45	DATA-B2	45	18	P2	
46	S.GND	46	*	GND	
47	DATA-B1	47	16	P1	
48	S.GND	48	*	GND	
49	DATA-B0	49	15	P0	
50	S.GND	50	*	GND	
51	/VSYNC	51	11	FLM	
52	S.GND	52	9	GND	
53	/HSYNC	53	10	LP	
54	S.GND	54	6	GND	
55	/BLANK	55	7	M	
56	S.GND	56	12	GND	
57	/DCLK	57	13	SHFCLK	
58	S.GND	58	14	GND	
59	N.C.	59	-	-	
60	S.GND	60	*	GND	
61	DISPEN	61	4	ENVCC	
62	S.GND	62	*	GND	
63	N.C.	63	-	-	
64	B-CNT0	64	-	-	Connect to 5k Ω pot.
65	B-CNT1	65	-	-	Connect to 5k Ω pot.
66	B-CNT2	66	-	-	Connect to 5k Ω pot. (Center pin)
67	HQEN	67	-	-	+5V = High q. (otherwise GND)
68	N.C.	68	-	-	

* pin 17, 20, 23, 26, 29, 32 35, 38, 45 and 50