

Display type: IBM ITXG60D
 Inverter no.: not available
 Cable no.: not available
 System: 686LCD with Panellink V4 (SW 2 & 3 = ON)
 Display driver: IBM ITXG60D 2 x 18, 5V
 Status: Verified

Display	LCD-conn. 1	JPLCD	100-pole con.	Remarks
Function	Pin	Pin	Function	
GND	1	*	GND	
-DTCLK	2	13	BSHCLK	Data Clock
GND	3	*	GND	
HSYNC	4	10	BLP	
VSYNC	5	11	BFLM	
GND	6	*	GND	
GND	7	*	GND	
GND	8	*	GND	
ER0	9	33	P12	
ER1	10	34	P13	
ER2	11	36	P14	
GND	12	*	GND	
ER3	13	37	P15	
ER4	14	41	P16	
ER5	15	42	P17	
GND	16	*	GND	
GND	17	*	GND	
GND	18	*	GND	
EG0	19	24	P6	
EG1	20	25	P7	
EG2	21	27	P8	
GND	22	*	GND	
EG3	23	28	P9	
EG4	24	30	P10	
EG5	25	31	P11	
GND	26	*	GND	
GND	27	*	GND	
GND	28	*	GND	
EB0	29	15	P0	
EB1	30	16	P1	
EB2	31	18	P2	
GND	32	*	GND	
EB3	33	19	P3	
EB4	34	21	P4	
EB5	35	22	P5	
GND	36	*	GND	
+DSPTMG	37	7	BM	Display timing
Reserved	38			N.C.
VDD	39	1	LCDVCC	+5V
VDD	40	2	LCDVCC	+5V
Reserved	41			N.C.

* = PIN 6,9,12,14,17,20,23,26,29,32,35,38,45,50,53,56,59,62,65 & 68

Display	LCD-conn. 2	JPLCD	50-pole conn.	Remarks
Function	Pin	Pin	Function	
GND	1	*	GND	
OR0	2	60	P30	
OR1	3	61	P31	
OR2	4	63	P32	
GND	5	*	GND	
OR3	6	64	P33	
OR4	7	66	P34	
OR5	8	67	P35	
GND	9	*	GND	
OG0	10	51	P24	
OG1	11	52	P25	
OG2	12	54	P26	
GND	13	*	GND	
OG3	14	55	P27	
OG4	15	57	P28	
OG5	16	58	P29	
GND	17	*	GND	
OB0	18	43	P18	
OB1	19	44	P19	
OB2	20	46	P20	
GND	21	*	GND	
OB3	22	47	P21	
OB4	23	48	P22	
OB5	24	49	P23	
GND	25	*	GND	
Reserved	26			N.C.
Reserved	27			N.C.
GND	28	*	GND	
Reserved	29			N.C.
Reserved	30			N.C.
Reserved	31			N.C.

* = PIN 6,9,12,14,17,20,23,26,29,32,35,38,45,50,53,56,59,62,65 & 68