

Display type: Sharp LQ14D311
 Cable no.: Not available
 System: 486-586LCD with FPUM-1 and AC-1
 Display driver:SHA LQ10D021
 Status: Not verified

Display	CN1 (15-pole)	Cable	JPLCD	connector	Remarks
Pin no.	Function	Wire no.	Pin	Function	
1	CLK	1	13	SHFCLK	Dot clock
2	GND	2	14	GND	
3	Hsync	3	10	LP	
4	Vsync	4	11	FLM	
5	R3	5	34	P13	
6	R4	6	36	P14	
7	R5	7	37	P15	
8	GND	8	35	GND	
9	G3	9	27	P8	
10	G4	10	28	P9	
11	G5	11	30	P10	
12	GND	12	29	GND	
13	B3	13	18	P2	
14	B4	14	19	P3	
15	B5	15	21	P4	

Display	CN2 (6-pole)	Cable	JPLCD	connector	Remarks
Pin no.	Function	Wire no.	Pin	Function	
1	VCC	1	1	VCC	
2	VCC	2	2	VCC	
3	GND	3	6	GND	
4	GND	4	12	GND	
5	ENAB	5	7	M	
6	TST	6	-	-	No connection

Display	CN3 (14-pole)	Cable	JPLCD	connector	Remarks
Pin no.	Function	Wire no.	Pin	Function	
1	R0	1	32	GND	not in use
2	R1	2	31	P11	
3	R2	3	33	P12	
4	GND	4	26	GND	
5	G0	5	22	P5	
6	G1	6	24	P6	
7	G2	7	25	P7	
8	GND	8	17	GND	
9	B0	9	20	GND	not in use
10	B1	10	15	P0	
11	B2	11	16	P1	
12	TST	12	-	-	No connection
13	TST	13	-	-	No connection
14	TST	14	-	-	No connection