

Display type: Kyocera KCB8060ESTT-X1
 Inverter type: LUNA X950003/A
 Cable type: 40860014
 System: 486-586LCD/S, FPUM-3 and AC-2
 Display driver: KYO KCB8060ESTT-X1
 Status: Verified

Display	CN1	CPU (JPLCD)		Remarks
Function	Pin no.	Pin no.	Function	
HD7	1	15	P0	Display data (upper column)
HD6	2	16	P1	
HD5	3	18	P2	
HD4	4	19	P3	
HD3	5	27	P8	
HD2	6	28	P9	
HD1	7	30	P10	
HD0	8	31	P11	
VSS	9	12	GND	
CP	10	13	SHFCLK	
VSS	11	14	GND	
LOAD	12	10	HSYNC	
DISP	13	4	ENVCC	
NC	14	-	-	No Connection
FRM	15	11	VSYNC	

Display	CN2	CPU (JPLCD)		Remarks
Function	Pin no.	Pin no.	Function	
VCONT	1	40	VEE	LCD adjust voltage
NC	2	-	-	No Connection
NC	3	-	-	No Connection
VSS	4	9	GND	
VSS	5	6	GND	
VDD	6	1	VCC	
LD7	7	21	P4	Display data (lower column)
LD6	8	22	P5	
LD5	9	24	P6	
LD4	10	25	P7	
LD3	11	33	P12	
LD2	12	34	P13	
LD1	13	36	P14	
LD0	14	37	P15	