

Display type: Sharp LM32010P
 Inverter no.: Not available
 Cable no.: Not available
 System: 686LCD with FPUM-2 and AC-2
 Display driver: SHA LM64K836
 Status: Not verified

Display Connector		JPLCD connector		Remarks
Term. #	Function	Pin	Connector	
1	S	11	FLM	Scan start-up signal
2	CP1	10	LP	Input data latch signal
3	CP2	13	SHFCLK	Data input clock signal
4	VDD	1	VCC	Power supply for logic and LCD (+5V)
5	VSS	14	GND	
6	VEE	40	VEE	
7	D0	19	P3	
8	D1	18	P2	
9	D2	16	P1	
10	D3	15	P0	
11	VR1	-	-	to 200K Ω potentiometer
12	VR2	-	-	to 200K Ω potentiometer