

Display type: Sharp LM80C31
 Inverter no.: not available
 Cable no.: not available
 System: 686LCD, FPUM-3 and AC-2
 Display driver: 800x600STNa, 5V
 Status: Not verified

Display	LCD-conn.	JPLCD	50-pole conn.	Remarks
Function	Pin	Pin	Function	
VSS	1	12	GND	
XCK	2	13	SHFCLK	
VSS	3	14	GND	
VSS	4	9	GND	
LP	5	10	LP	
YD	6	11	FLM	
VSS	7	6	GND	
VSS	8	6	GND	
VDD	9	1	VCC	
DISP	10	4	ENVCC	
VSS	11	17	GND	
VSS	12	17	GND	
VSS	13	20	GND	
DL7	14	21	P4	
DL6	15	22	P5	
DL5	16	24	P6	
DL4	17	25	P7	
DL3	18	33	P12	
DL2	19	34	P13	
DL1	20	36	P14	
DL0	21	37	P15	
VSS	22	38	GND	
VSS	23	32	GND	
VSS	24	32	GND	
DU0	25	31	P11	
DU1	26	30	P10	
DU2	27	28	P9	
DU3	28	27	P8	
DU4	29	19	P3	
DU5	30	18	P2	
DU6	31	16	P1	
DU7	32	15	P0	
VSS	33	23	GND	
VSS	34	26	GND	
VSS	35	29	GND	
VDD	36	2	VCC	
VDD	37	2	VCC	
VCON	38	40	VEE	
NC	39	-	-	No Connection
VSS	40	35	GND	

VSS	41	35	GND	
-----	----	----	-----	--